

Setting up Vodafone GPRS/3G, WAP and MMS on a Smartphone device

This article applies to the Smartphone 2003 and Windows Mobile 5.0 platforms

Setting up the GPRS/3G Connection

From the home screen press **Start**
Select the **Settings** icon
Scroll down and select **Connections**
Scroll down and select **GPRS**
Press **Menu** and select **Add**
In the Description: field enter **Vodafone**
In the Connects to: field select **The Internet**
In the Access Point: field enter **internet**
In the User name: field enter **web**
In the Password: field enter **web**
Leave the Primary or Secondary DNS fields **blank**
Leave the IP address field **blank**
Select **Done**

Setting up the WAP Connection

Press **Menu** and select **Add**
In the Description: field enter **Vodafone MMS**
In the Connects to: field select **Work**
In the Access Point: field enter **wap.vodafone.co.uk**
In the User name: field enter **wap**
In the Password: field enter **wap**
Leave the Primary or Secondary DNS fields **blank**
Leave the IP address field **blank**
Select **Done** twice
Scroll down and select **Proxy**
Press **Menu** and select **Add**
In the Description: field enter **Vodafone MMS**
In the Connects from: field select **Work**
In the Connects to: field select **WAP Network**
In the Proxy field enter **212.183.137.012:8799**
In the Type: field select **HTTP**
Leave User name and Password **Blank**
Select **Done** 4 times

Setting up the MMS Account

Select the **Messaging** icon
Scroll down and select **MMS**
Select **Menu**
Select **Options**
Scroll down and select **Account Settings**
Scroll down to the bottom of the page to Photo Resolution: and select **VGA (640x480)**
Press **Menu** and select **MMSC Settings**
Press **Menu** and select **Edit**

In the Name field enter **Vodafone MMS**
In the MMSC URL field enter <http://mms.vodafone.co.uk/servlets/mms>
In the WAP Gateway field enter **212.183.137.012**
In the Port field enter **9201**
In the Connect Via: field select **Work**
In the WAP Version: field select **WAP 1.2**
In the Max. Sending Size: field select **300K**
Press **Done**
Press the **Home** key

Your device has now been configured