

# Setting up Three Internet and MMS on a Smartphone device

This article applies to the Smartphone 2003 and Windows Mobile 5.0 platforms

## Setting up the 3G Connection

From the home screen press **Start**  
Select the **Settings** icon  
Scroll down and select **Connections**  
Scroll down and select **GPRS,3G**  
Press **Menu** and select **Add**  
In the Description: field enter **Three**  
In the Connects to: field select **The Internet**  
In the Access Point: field enter **three.co.uk**  
Leave the Username and Password fields **blank**  
Leave the Primary or Secondary DNS fields **blank**  
Leave the IP address field **blank**  
Select **Done**

## Setting up the MMS Connection

Press **Menu** and select **Add**  
In the Description: field enter **Three MMS**  
In the Connects to: field select **Work**  
In the Access Point: field enter **three.co.uk**  
Leave the Username and Password fields **blank**  
Leave the Primary or Secondary DNS fields **blank**  
Leave the IP address field **blank**  
Select **Done** twice  
Scroll down and select **Proxy**  
Press **Menu** and select **Add**  
In the Description: field enter **Three MMS**  
In the Connects from: field select **Work**  
In the Connects to: field select **WAP Network**  
In the Proxy field enter **217.171.129.002:8799**  
In the Type: field select **HTTP**  
Leave User name and Password **Blank**  
Select **Done** 4 times

Select the **Messaging** icon  
Scroll down and select **MMS**  
Select **Menu**  
Select **Options**  
Scroll down and select **Account Settings**  
Scroll down to the bottom of the page to Photo Resolution: and select **VGA (640x480)**  
Press **Menu** and select **MMSC Settings**  
Press **Menu** and select **Edit**  
In the Name field enter **Three MMS**  
In the MMSC URL field enter <http://mms.um.three.co.uk:10021/mmsc>  
In the WAP Gateway field enter **217.171.129.002**  
In the Port field enter **9201**  
In the Connect Via: field select **Work**  
In the WAP Version: field select **WAP 1.2**

In the Max. Sending Size: field select **300K**  
Press **Done**  
Press the **Home** key

Your device has now been configured