

Setting up Three Internet and MMS on a Pocket PC device

This article applies to the Pocket PC 2003 and Windows Mobile 5.0 platforms

Setting up the Internet connection

Tap on **Start** and select **Settings**

Tap on the **Connections** tab at the bottom of the screen

Tap on the **Connections** icon

In the **My ISP** section, tap on the option to **Add a new modem connection**

In the **Name** field, type in **Three 3G**

In the **Modem** field, select **Cellular Line (GPRS,3G)**

Tap **Next**

In the **Access Point Name** field, type in **three.co.uk**

Tap **Next**

Leave the **Username**, **Password** and **Domain** fields blank

Tap **Finish**

Setting up the MMS connection

Tap on **Start** and select **Settings**

Tap on the **Connections** tab at the bottom of the screen

Tap on the **Connections** icon

In the **My Work Network** section, tap on the option to **Add a new modem connection**

In the **Name** field, type in **Three MMS**

In the **Modem** field, select **Cellular Line (GPRS,3G)**

Tap **Next**

In the **Access Point Name** field, type in **three.co.uk**

Tap **Next**

Leave the **Username**, **Password** and **Domain** fields blank

Tap **Finish**

In the **My Work Network** section, tap on the option to **Manage existing connections**

Tap on the **Proxy Settings** tab at the bottom of the screen

Tick the option **This network connects to the Internet**

Tick the option **This network uses a proxy server to connect to the Internet**

Tap on the **Advanced** button

Tap on the entry for **WAP**

In the **Server** field enter **217.171.129.002**

In the **Port** field enter **8799**

Leave the **User Name**, **Password** and **Domain** fields blank.

Tap **OK** 3 times to save the settings

Setting up the MMS account

Tap on **Start** and select **Messaging**

Tap on the **Menu** button and select **MMS Configuration**

On the **Preferences** tab, scroll down to **Photo Resolution**. Set the option to **VGA (640x480)**

Tap on the **Servers** tab at the bottom of the screen

Tap on the **New** button

In the **Server Name** field enter **Three MMS**

In the **Gateway** field enter **217.171.129.002**

In the **Port Number** field enter **9201**

In the **Server Address** field enter <http://mms.um.three.co.uk:10021/mmsc>

In the **Connect Via** field, select **Three MMS**
Set the **Sending size limitation** to **250K**
Set the **WAP Version** to **WAP 1.2**
Tap **OK**
Tap the **Set As Default** button
Tap **OK**

Your device has now been configured.